

4 Move Machine to power on to perform automatic self test	4.1 Coffee machine is not working (does not function)	a) YES - power cord is okay (loose connection)	YES - continue NO - replace power cord
		b) YES - On/Off switch has typical switching noise	YES - continue NO - replace functional block
		c) YES - pump works (press a coffee button)	YES - continue with point e) NO - continue with point d)
		d) YES - both coffee buttons are working	YES - replace pump NO - replace functional block
		e) YES - fine wire fuses or triac on thermoblock defective	YES - replace thermoblock NO - continue
		f) YES - wiring is okay NO - continue with point 4.2	YES - replace functional block NO - replace defective cables
	4.2 Both coffee buttons are blinking 3x fast	YES - thermoblock is hot NO - self test ok - continue	YES - switch off/on coffee machine and check again NO - replace thermoblock or functional block