



- Q401-Q404
  - 2SK369
  - Q405
  - NJM2041DD
  - QV01
  - 2SC1627 (0,Y)
  - QV02
  - 2SA817 (0,Y)
  - QN01, QN02,
  - 2SC2240
  - QN03
  - 2SA970
  - QN04
  - TA7317P
  - Q701, Q702,
  - uPC1270H
  - Q703, Q704,
  - 2SC3419Y
  - Q709, Q710,
  - 2SC3180 (R,0)
  - Q711, Q712,
  - 2SA1263 (R,0)
  - Q801
  - NJM78M24A
  - DS01
  - 5.1V
  - DV04, DV05
  - DV08, DV09, DN03,
  - D401, DV01, DB03
  - 1S133 etc.
  - DV02, DV03
  - 15V
  - DY01 - DY06
  - LT3D8B
  - DY07
  - LT3G8B
  - DN01, DN02,
  - 1SS81
  - DB01
  - S4VB20
  - DB02
  - DSF10C
- TOP VIEW**  
 1 8  
 4 5  
 NJM2041DD
- SIDE VIEW**  
 INPUT OUTPUT  
 GND NJM78M24A
- E C B  
 B E C  
 D G S  
 S D  
 G D  
 E C B  
 B C E  
 B C E  
 B C E  
 B C E
- FRONT VIEW**  
 1 12  
 uPC1270H

**NOTE ON PARTS :**

BOARD	PART	IN SCHEMATIC	ON BOARD
P701	R801, R808	68 (2W)	47 (2W)
	R809	33 (1/4W)	220 (1/4W)
	C806	0.47/50V	4.7/50
PS01	C703, C704	Elco. polar	Elco. bipolar
	RS01, RS02	6.8k	5.6k
	RS03, RS04	6.8k	47k
	CS01, CS02	0.082uF	0,056uF
	CS03, CS04	1000p	470p
PE01	CE05, CE06	Elco. polar	Elco. bipolar

**NOTE ON SAFETY :**  
 Symbol ⚠ Fire or electrical shock hazard. Only original parts should be used to replace any part marked with symbol ⚠. Any other component substitution (other than original type), may increase risk of fire or electrical shock hazard.

"SERVICE INFORMATION IS FOR USE BY QUALIFIED PERSONEL ONLY - ANY MISADJUSTMENT OR MISALIGNMENT MAY BE TREATED AS NON-WARRANTY REPAIR BY ANY MARANTZ SERVICE CENTRE."

- Kind of Common Parts**
- RESISTOR**
- R\*\*\* (1) GD05 - - 140, Carbon film fixed resistor, ±5% 1/4W
  - R\*\*\* (2) GD05 - - 140, Carbon film fixed resistor, ±5% 1/6W
- CERAMIC CAP.**
- C\*\*\* (1) DD1 - - 370, Ceramic condenser, disc type (titan condenser) Temp. coeff. P350 ~ N1000 50V
  - C\*\*\* (1) DK16 - - 300, High dielectric constant ceramic condenser, disc type (titan variable) Temp. chara. 2B4 50V
- ELECTROLYTIC CAP. (⊖) / FILM CAP. (⊕)**
- (1) EA - - - 10, Electrolytic condenser, one-way lead type, tolerance ±20%
  - (2) DF15 - - 350, Plastic film condenser, one-way type, Mylar, ±5% 50V

In case of ordering the common parts, please establish the correct parts number of 10 figures by the procedure "ASSIGNMENT OF COMMON PARTS CODES"